



Fibaro Double Switch 2 - Switch

wireless - Z-Wave - Z-Wave Plus - 868.4 MHz - 908.4 MHz - 908.42 MHz - 916 MHz - 869.8 MHz - 921.4 MHz - 869 MHz - 919.8 MHz

Group	Home Automation
Manufacturer	Fibaro
Manufacturer item no.	FIBEFGS-223
EAN/UPC	5902020528661

Description

Fibaro Switch 2 is designed to be installed in standard wall switch boxes or anywhere else where it is necessary to control electric devices. Fibaro Switch 2 allows to control connected devices either via the Z-Wave+ network or via a switch connected directly to it and is equipped with active power and energy consumption metering functionality.

Main features

Product Description	Fibaro Double Switch 2 - switch
Product Type	Switch
Connectivity	Wireless - Z-Wave, Z-Wave Plus
Frequency Band	868.4 MHz, 908.4 MHz, 908.42 MHz, 916 MHz, 869.8 MHz, 921.4 MHz, 869 MHz, 919.8 MHz
Dimensions (WxDxH)	3.825 cm x 4.25 cm x 2.03 cm

Extended details

General	
Product Type	Switch
Connectivity Technology	Wireless - Z-Wave, Z-Wave Plus
Max Range Indoors	40 m
Max Range Open Space	50 m
Frequency Band	868.4 MHz, 908.4 MHz, 908.42 MHz, 916 MHz, 869.8 MHz, 921.4 MHz, 869 MHz, 919.8 MHz
Features	Overcurrent protection, overheat protection
Miscellaneous	
Encryption Algorithm	128-bit AES
Nominal Voltage	AC 120/230 V
Compliant Standards	FCC Part 15, IC, RoHS 2011/65/EU, EMC 2014/30/EU, LVD 2014/35/EU, R&TTE Directive 1999/5/EC
Dimensions & Weight	



Width	3.825 cm
Depth	4.25 cm
Height	2.03 cm
Environmental Parameters	
Min Operating Temperature	0 °C
Max Operating Temperature	35 °C

Technical data © CNET Content Solutions. Subject to technical modifications and errors.