

MPN: MBXSA-AC0002

## 42W, 14V, 3A, 6.5/4.4mm, Samsung

14V 3A Plug: 6.5\*4.4 Including Power Cord

- Premium Build Quality
- Full Compatibility With Oem Devices
- Certified Safety And Protection Features
- Wide Product Portfolio
- Compact And Robust Design
- 12-Month Full Reliable Warranty
- Satisfaction Guarantee With Exchange Option



## Caractéristiques

|                              |                                         |            |
|------------------------------|-----------------------------------------|------------|
| Autres caractéristiques      | Piles fournies                          | Non        |
|                              | Protection contre les court circuits    | Oui        |
|                              | Protection contre les surcharges        | Oui        |
| Caractéristiques             | Certification                           | CE         |
|                              | Compatibilité de marque                 | Samsung    |
|                              | Connecteurs d'énergie détachable        | Oui        |
|                              | Couleur du produit                      | Noir       |
|                              | Fréquence d'entrée                      | 50 - 60 Hz |
|                              | Matériau du boîtier/corps               | Plastic    |
|                              | Puissance de sortie                     | 42 W       |
|                              | Tension d'entrée                        | 110-230 V  |
|                              | Tension de sortie                       | 14 V       |
|                              | Tension de sortie réglable              | Non        |
|                              | Type d'alimentation d'énergie           | Intérieur  |
|                              | Type d'énergie courante                 | CA vers CC |
|                              | Utilité                                 | Moniteur   |
| Contenu de l'emballage       | Types de fiches d'alimentation fournies | EU         |
| Design                       | Bouton marche/arrêt intégré             | Non        |
|                              | Couleur du boîtier                      | Noir       |
| Détails techniques           | Consommation d'énergie (mode veille)    | 0,1 W      |
|                              | Dimensions fiche 1                      | 6.5*4.4 mm |
|                              | Puissance                               | 42 W       |
| Informations sur l'emballage | Câbles inclus                           | Secteur    |
|                              | Quantité                                | 1 pièce(s) |
|                              | Type d'emballage                        | Box        |

**Puissance**

|                                                |       |
|------------------------------------------------|-------|
| Ajustement de la tension de sortie automatique | Oui   |
| Courant de sortie de l'adaptateur secteur      | 3 A   |
| Tension de voltage à l'entrée (min)            | 100 V |

**représentation /  
réalisation**

|               |         |
|---------------|---------|
| Connecteur(s) | 6.5*4.4 |
|---------------|---------|

**Vendor information**

|            |             |
|------------|-------------|
| Brand Name | CoreParts   |
| Warranty   | 1 Année (s) |